

D520E Vandal-proof Dome IP Camera



- ▶ Progressive scan
- ▶ Simultaneous MPEG-4 and Motion JPEG
- ▶ Vari-focal lens
- ▶ Power over Ethernet
- ▶ IP66 rated rugged housing

- Progressive scan CMOS
- Simultaneous MPEG-4 and Motion JPEG
- 30 frames per second in all resolutions
- 3.7 – 12mm, F1.4 vari-focal lens
- Excellent low-light performance with enhanced night mode
- Two-way audio
- Power over Ethernet (IEEE 802.3af)
- 1 x alarm input, 1 x alarm output
- IP66 rated weatherproof and vandalproof housing
- SSL v3 advanced HTTPS encryption
- 3GPP mobile surveillance
- Easy access via Windows Live Messenger
- Multi-lingual user interface
- 16 channel surveillance software

ZAVIG

Technical Specifications

Models	D520E
Image sensor	1/4" Progressive scan CMOS sensor
Lens	F1.4, 3.7 ~ 12 mm, Vari-focal lens
Angle of view	19° ~ 56° horizontal
Digital Zoom	10x digital
Min Illumination	0.5 Lux
S/N Ratio	50 dB
Video	Motion JPEG
Compression	MPEG-4 Part2 (ISO/IEC 14496-2), Profile: SP
Resolutions	Motion JPEG: 3 resolutions from 640x480 to 160x120 via API, 3 resolutions via configuration web page MPEG-4: 3 resolutions from 640x480 to 160x120 via API, 3 resolutions via configuration web page
Frame rate	Motion JPEG: Up to 15 fps at 640x480 (4:3 resolution) MPEG-4: Up to 30 fps at 640x480 (4:3 resolution)
Video streaming	Simultaneous Motion JPEG and MPEG-4 (Dual streaming) Controllable Frame rate and bandwidth Support Unicast and Multicast Support 3GPP/ISMA RTSP (Real Time Streaming Protocol)
Image settings	Rotation: Mirror, Flip, Mirror Flip brightness, contrast, saturation, hue Overlay capabilities: time, date, text and privacy image
Shuttle time	1/7.5 ~ 1/120 sec.
Audio	Two-way (full duplex) External microphone input or line input Audio compression: G.711 PCM, 8kHz, 64 kbit/s
Security	Multiple user access levels with password protection, HTTPS encryption
Users	5 simultaneous users Unlimited number of users using multicast
Alarm	Alarm input 5V/12V DC
Input/Output	Alarm output Max 30W
Instant Messenger	Support MSN Live View

Alarm and event management	Input: alarm buffer, alarm input, motion detection Output: FTP, SMTP, HTTP event, alarm output Pre-and post alarm buffer
Connectors	RJ-45 for Ethernet 10/100 Base-T (with PoE) Terminal blocks for DC power Terminal blocks for 1 alarm input, 1 output Reset push switch Terminal blocks for Line mono input, Terminal blocks for Line stereo output
Casing	Aluminum casing
Power	12V DC, 1A, Max 12W PoE (Power over Ethernet) Built-in IEEE 802.3af
Operating conditions	Warm Start: -30°C (-22 °F) to 50°C (122 °F) Cold Start: 0°C (32 °F) to 50°C (122 °F) Humidity 20 ~ 80% RH (non-condensing)
Installation, management, and maintenance	ZAVIO Camera Management tool on CD and web-based configuration. Configuration of backup and restore Firmware upgrades over HTTP, firmware available at www.zavio.com
Minimum web browsing requirement	Pentium 4 1.8GHz (or equivalent AMD) 64 MB RAM graphic cards (or equivalent on-board graphic cards) 512 MB RAM Windows 2000, 2003, XP or Vista Mac OS Leopard 10.5
Supported protocols	Bonjour, TCP/IP, DHCP, PPPoE, ARP, ICMP, FTP, SMTP, DNS, NTP, UPnP, RTSP, RTP, RTCP, HTTP, TCP, UDP, 3GPP/ISMA RTSP
Included accessories	Quick Installation Guide, CD (IP Surveillance Software, Intelligent IP Installer, User Manuals, and Language Pack), mounting and connector kits, power supply 12V DC
Video management software	ZAVIO Intelligent IP Installer_ Video management software, for viewing, recording and archiving up to 16 cameras See http://www.zavio.com/support.htm for more software application
Approvals	CE, FCC, RoHS
Accessory (not included)	Wall mounting Bracket
Dimensions and weight	115 x 144 (φ)mm (4.5" x 5.6") 1040 g (2.3 lb) excl. power supply

Physical Description

